



IP Office

IP Office ContactStore 7.8

Notice

While reasonable efforts were made to ensure that the information in this document was complete and accurate at the time of printing, Avaya Inc. can assume no liability for any errors. Changes and corrections to the information in this document may be incorporated in future releases.

Documentation Disclaimer

Avaya Inc. is not responsible for any modifications, additions, or deletions to the original published version of this documentation unless such modifications, additions, or deletions were performed by Avaya.

Link Disclaimer

Avaya Inc. is not responsible for the contents or reliability of any linked Web sites referenced elsewhere within this Documentation, and Avaya does not necessarily endorse the products, services, or information described or offered within them. We cannot guarantee that these links will work all of the time and we have no control over the availability of the linked pages.

License

USE OR INSTALLATION OF THE PRODUCT INDICATES THE END USER'S ACCEPTANCE OF THE TERMS SET FORTH HEREIN AND THE GENERAL LICENSE TERMS AVAILABLE ON THE AVAYA WEBSITE AT <http://support.avaya.com/LicenseInfo/> ("GENERAL LICENSE TERMS"). IF YOU DO NOT WISH TO BE BOUND BY THESE TERMS, YOU MUST RETURN THE PRODUCT(S) TO THE POINT OF PURCHASE WITHIN TEN (10) DAYS OF DELIVERY FOR A REFUND OR CREDIT.

Avaya grants End User a license within the scope of the license types described below. The applicable number of licenses and units of capacity for which the license is granted will be one (1), unless a different number of licenses or units of capacity is specified in the Documentation or other materials available to End User. "Designated Processor" means a single stand-alone computing device. "Server" means a Designated Processor that hosts a software application to be accessed by multiple users. "Software" means the computer programs in object code, originally licensed by Avaya and ultimately utilized by End User, whether as stand-alone Products or pre-installed on Hardware. "Hardware" means the standard hardware Products, originally sold by Avaya and ultimately utilized by End User.

License Type(s): Designated System(s) License (DS).

End User may install and use each copy of the Software on only one Designated Processor, unless a different number of Designated Processors is indicated in the Documentation or other materials available to End User. Avaya may require the Designated Processor(s) to be identified by type, serial number, feature key, location or other specific designation, or to be provided by End User to Avaya through electronic means established by Avaya specifically for this purpose.

Copyright

Except where expressly stated otherwise, the Product is protected by copyright and other laws respecting proprietary rights. Unauthorized reproduction, transfer, and or use can be a criminal, as well as a civil, offense under the applicable law.

Third-Party Components

Certain software programs or portions thereof included in the Product may contain software distributed under third party agreements ("Third Party Components"), which may contain terms that expand or limit rights to use certain portions of the Product ("Third Party Terms"). Information identifying Third Party Components and the Third Party Terms that apply to them is available on Avaya's web site at: <http://support.avaya.com/ThirdPartyLicense/>

Avaya Fraud Intervention

If you suspect that you are being victimized by toll fraud and you need technical assistance or support, call Technical Service Center Toll Fraud Intervention Hotline at +1-800-643-2353 for the United States and Canada. Suspected security vulnerabilities with Avaya Products should be reported to Avaya by sending mail to: securityalerts@avaya.com. For additional support telephone numbers, see the Avaya Support web site (<http://www.avaya.com/support>).

Trademarks

Avaya and the Avaya logo are registered trademarks of Avaya Inc. in the United States of America and other jurisdictions. Unless otherwise provided in this document, marks identified by "®," "TM" and "SM" are registered marks, trademarks and service marks, respectively, of Avaya Inc. All other trademarks are the property of their respective owners.

Documentation information

For the most current versions of documentation, go to the Avaya Support web site (<http://www.avaya.com/support>) or the IP Office Knowledge Base (<http://marketingtools.avaya.com/knowledgebase/>).

Avaya Support

Avaya provides a telephone number for you to use to report problems or to ask questions about your contact center. The support telephone number is 1 800 628 2888 in the United States. For additional support telephone numbers, see the Avaya Web site: <http://www.avaya.com/support>.

1. Search and Replay

ContactStore performs replay of recordings by means of a browser-based application that is accessible with Internet Explorer (IE) V5.0 and higher. The Search and Replay page includes the following features:

- Personal security restrictions. The restrictions are applied as you log into the web server.
- Criteria-based searches. Use the Search filter fields to perform specific searches.
- Calls matching your requested search appear in the right-hand pane.
- Replay controls. Use the replay controls to start, stop, pause, skip forward, skip backward, or to export the recording to a readily playable .wav file.
- Audio waveform display. The waveform presents a graphic representation of the audio content of the call. Use the waveform to avoid replaying static or silences, and to move easily to specific portions of a call.

1.1 Accessing Search and Replay

Internet Explorer is used to view the Search and Replay application.

1. Enter the URL for the ContactStore server in the form: *http://myservername:8888*, replacing *myservername* with the IP address or host name of the ContactStore. To use the host name, it must be entered into your DNS server.
2. Enter your Username and Password.
 - If you are already logged on as a Windows user and this account has been entered into ContactStore, you will immediately access the application.
 - If this is your first time logging on, or if the password has just been reset, the password field is ignored. However, before you can continue, you must change your password.
3. If your user account has administration privileges, the Administration page is displayed when you log in. Use the link at the top left to access the Search and Replay page. The Search and Replay page also provides a link to return to the administration pages. Otherwise, once you log in, the Search and Replay page is displayed:

AVAYA ContactStore
powered by Verint Systems

Help | About
Change Password
Logout

Administration
Administer System

Search Filters

Call Start Range
02/03/09 00:00:00
20/05/09 23:59:59

Parties
Length
Target Number
Call Set
SEARCH

Results
1 2 Next Show All Select All Select None

Call Start	Len	Parties	Type	Target	
24/04/09 02:13:54	00:15	2205 (Extn2205), 2207 (Extn2207)	Outgoing	2207	<input checked="" type="checkbox"/>
24/04/09 02:14:26	00:12	3103 (Extn3103), 2205 (Extn2205)	Incoming	2205	<input checked="" type="checkbox"/>
24/04/09 02:24:27	00:09	2205 (Extn2205), 2207 (Extn2207)	Outgoing	2207	<input checked="" type="checkbox"/>
24/04/09 02:25:19	00:12	3103 (Extn3103), 2205 (Extn2205)	Incoming	2205	<input type="checkbox"/>
28/04/09 00:37:53	00:05	2205 (Extn2205), 2207 (Extn2207)	Outgoing	2207	<input type="checkbox"/>
20/05/09 06:42:51	00:05	3105 (Extn3105), 2205 (Extn2205)	Incoming	2205	<input type="checkbox"/>
20/05/09 06:43:08	00:06	3105 (Extn3105), 2205 (Extn2205)	Incoming	2205	<input type="checkbox"/>
20/05/09 06:43:27	00:10	3105 (Extn3105), 2205 (Extn2205)	Incoming	2205	<input type="checkbox"/>
20/05/09 06:44:08	00:09	2207 (Extn2207), 2205 (Extn2205)	Incoming	2205	<input type="checkbox"/>
20/05/09 06:44:32	00:07	2207 (Extn2207), 2205 (Extn2205)	Incoming	2205	<input type="checkbox"/>

1.2 Searching for Calls

Search filters can be used to find specific records. As you search for calls, keep in mind:

- Searching on the basis of the details of one or more of the "parties" involved in the call is the most common way to find the calls you are looking for. This will find calls to or from a station, number, or name (partial or entire) that you enter.
- You will find that Incl (includes) is the most useful search method when searching for calls involving specific parties.
- If you select the blank option in the drop-down box, any existing entry in the text box next to it will be retained. It won't be applied to the current search, but it makes it easy to add it back into the search criteria later.
- If a recording has a blank entry for a field, it is listed as "N/A" (not available). You cannot, however, search for such records by specifying "starts with N" or "ends with A" or "includes N/A" in the Search field; this tag is not present in the database.

To search for calls:

1. Use the calendar controls at the upper left to specify the date and time range. Time and date reference when the call segment started.

Search Filters

Call Start Range

24/04/04 00:00:00

24/08/04 23:59:59

Parties

Length

Target Number

SEARCH

2. Use the drop-down boxes for each criterion, for example, Parties, to specify the operand, such as = equals (numeric fields only).

The drop-down box lists the following operands:

Drop-down	Meaning
	No criteria
=	Equals (numeric fields only)
<	Less than (numeric fields only)
>	Greater than (numeric fields only)
Incl	Includes or Contains (string fields only)
Starts	Starts with (string fields only)
Ends	Ends with (string fields only)

3. In the corresponding text box, enter the specific criterion, such as 3.
4. Select Search to execute the specified search.

1.3 Viewing Results

The example shows a typical result set. The Results list includes the following information:

- Call start time.
- Call length in minutes and seconds.
- Name (where available) and number of the parties on the call.
- Call type - incoming or outgoing.
- target number (the number dialed which may not be the same as the number that answered the call).

When you view the results you can:

- Click the page indicators (1 2 3 ... 8 Next) above the Results table to move through the list of results.
- Click the arrows within the column headers to sort the results by that column. A blue arrow indicates the active sort field and direction.

AVAYA ContactStore

[Help](#) | [About](#)
[Change Password](#)
[Logout](#)

powered by Verint Systems

Administration
[Administer System](#)

Search Filters

Call Start Range

02/03/09 00:00:00

20/05/09 23:59:59

Parties

Length

Target Number

Call Set

Results

1 2 Next Show All Select All Select None

	Call Start	Len	Parties	Type	Target	
<input type="radio"/>	24/04/09 02:13:54	00:15	2205 (Extn2205), 2207 (Extn2207)	Outgoing	2207	<input checked="" type="checkbox"/>
<input type="radio"/>	24/04/09 02:14:26	00:12	3103 (Extn3103), 2205 (Extn2205)	Incoming	2205	<input checked="" type="checkbox"/>
<input type="radio"/>	24/04/09 02:24:27	00:09	2205 (Extn2205), 2207 (Extn2207)	Outgoing	2207	<input checked="" type="checkbox"/>
<input type="radio"/>	24/04/09 02:25:19	00:12	3103 (Extn3103), 2205 (Extn2205)	Incoming	2205	<input type="checkbox"/>
<input type="radio"/>	28/04/09 00:37:53	00:05	2205 (Extn2205), 2207 (Extn2207)	Outgoing	2207	<input type="checkbox"/>
<input type="radio"/>	20/05/09 06:42:51	00:05	3105 (Extn3105), 2205 (Extn2205)	Incoming	2205	<input type="checkbox"/>
<input type="radio"/>	20/05/09 06:43:08	00:06	3105 (Extn3105), 2205 (Extn2205)	Incoming	2205	<input type="checkbox"/>
<input type="radio"/>	20/05/09 06:43:27	00:10	3105 (Extn3105), 2205 (Extn2205)	Incoming	2205	<input type="checkbox"/>
<input type="radio"/>	20/05/09 06:44:08	00:09	2207 (Extn2207), 2205 (Extn2205)	Incoming	2205	<input type="checkbox"/>
<input type="radio"/>	20/05/09 06:44:32	00:07	2207 (Extn2207), 2205 (Extn2205)	Incoming	2205	<input type="checkbox"/>

1.4 Call Sets


Call sets allow you to save the results of a search and to then be able to re-access that set of calls by name. You can then remove files from the call set or use other searches to add additional calls to the call set.

To create a call set

1. Perform a search.
2. Within the results, for those calls that you want included in the call set, select the check box on the right.

The screenshot shows the AVAYA ContactStore interface. On the left, there is a sidebar with 'Administration' and 'Search Filters'. The 'Search Filters' section includes fields for 'Call Start Range' (02/03/09 to 20/05/09), 'Parties', 'Length', 'Target Number', and 'Call Set'. A 'SEARCH' button is at the bottom of the sidebar. The main area displays 'Results' in a table with columns: Call Start, Len, Parties, Type, Target, and a checkbox. The table contains 10 rows of call records. At the top right of the results area, there are links for 'Help', 'About', 'Change Password', and 'Logout'. Below the table, there are 'Select All' and 'Select None' links.

Call Start	Len	Parties	Type	Target	
24/04/09 02:13:54	00:15	2205 (Extn2205), 2207 (Extn2207)	Outgoing	2207	<input checked="" type="checkbox"/>
24/04/09 02:14:26	00:12	3103 (Extn3103), 2205 (Extn2205)	Incoming	2205	<input checked="" type="checkbox"/>
24/04/09 02:24:27	00:09	2205 (Extn2205), 2207 (Extn2207)	Outgoing	2207	<input checked="" type="checkbox"/>
24/04/09 02:25:19	00:12	3103 (Extn3103), 2205 (Extn2205)	Incoming	2205	<input type="checkbox"/>
28/04/09 00:37:53	00:05	2205 (Extn2205), 2207 (Extn2207)	Outgoing	2207	<input type="checkbox"/>
20/05/09 06:42:51	00:05	3105 (Extn3105), 2205 (Extn2205)	Incoming	2205	<input type="checkbox"/>
20/05/09 06:43:08	00:06	3105 (Extn3105), 2205 (Extn2205)	Incoming	2205	<input type="checkbox"/>
20/05/09 06:43:27	00:10	3105 (Extn3105), 2205 (Extn2205)	Incoming	2205	<input type="checkbox"/>
20/05/09 06:44:08	00:09	2207 (Extn2207), 2205 (Extn2205)	Incoming	2205	<input type="checkbox"/>
20/05/09 06:44:32	00:07	2207 (Extn2207), 2205 (Extn2205)	Incoming	2205	<input type="checkbox"/>

3. Click on the  icon.

The modal dialog has two radio buttons: 'Add to existing Call Set' and 'Create new Call Set'. The 'Add to existing Call Set' option is selected. To its right is a dropdown menu. Below the 'Create new Call Set' option is a text input field. At the bottom right are 'Cancel' and 'Enter' buttons.


- To add the selected calls to an existing call set, select Add to existing Call Set and use the drop down list to select the call set. Click Enter.
- To add the selected calls to a new call set, select Create new Call Set. Enter a name for the call set and click Enter.

Viewing and Editing a Call Set

1. To display an existing call set, select the call set name from the Call Set drop down at the bottom left of the screen and click SEARCH. The calls in that call set are then displayed.


The screenshot shows the AVAYA ContactStore interface. On the left is the 'Administration' sidebar with 'Search Filters' including 'Call Start Range', 'Parties', 'Length', 'Target Number', and 'Call Set' (set to 'Sales Leads'). A 'SEARCH' button is at the bottom of the filters. The main area is titled 'Results' and contains a table of call records. At the top right of the results area are links for 'Select All' and 'Select None'.

Call Start	Len	Parties	Type	Target	
24/04/09 02:13:54 00:15	2205 (Extn2205), 2207 (Extn2207)	Outgoing	2207	<input type="checkbox"/>	
24/04/09 02:14:26 00:12	3103 (Extn3103), 2205 (Extn2205)	Incoming	2205	<input type="checkbox"/>	
24/04/09 02:24:27 00:09	2205 (Extn2205), 2207 (Extn2207)	Outgoing	2207	<input type="checkbox"/>	

2. To remove calls from the call set, select the check box next to the calls to be removed and then click on the  icon.

1.5 Playing a Call

When a call recording has been found you can play the recording.

1. Click the radio button to the left of the call you want to play, ie the column with the  icon.
2. The audio is retrieved from the server and an audio waveform is shown at the top of the screen. Audio retrieval may take a few seconds to a few minutes depending on the size of the file.









The screenshot shows the AVAYA ContactStore interface. At the top, there is a blue header with the AVAYA ContactStore logo, 'powered by Verint Systems', and a timestamp '02:14:30'. To the right of the header are links for 'Help', 'About', 'Change Password', and 'Logout'. Below the header, there is a navigation menu with 'Administration' and 'Search Filters'. The 'Search Filters' section includes a 'Call Start Range' with two date and time pickers. The main content area is titled 'Results' and contains a table with columns: 'Call Start', 'Len', 'Parties', 'Type', and 'Target'. The table has two rows of call data. Below the table, there is a small control panel with several icons for playback control.

Call Start	Len	Parties	Type	Target
24/04/09 02:14:26	00:12	3103 (Extn3103), 2205 (Extn2205)	Incoming	2205
24/04/09 02:24:27	00:09	2205 (Extn2205), 2207 (Extn2207)	Outgoing	2207

3. Click on the audio waveform to play it. Click anywhere in the audio waveform to play from that point in the call. Click just to the left of the audio waveform to play from the very beginning of the call.
4. Placing your mouse over the audio waveform displays a small control panel that you can use to control playback and to perform other actions:



-  Skip back.
-  Play.
-  Pause.
-  Skip forwards.
- The following additional options are only available for users who have May export recordings as files? enabled in their user account settings. These users can also [export multiple calls](#) at the same time.
 -  Save as .wav file.
 -  Email as .wav file.


1.6 Exporting Multiple Calls

Users who have the May export recordings as files? option enabled in their account can export calls. [They can export an individual call while playing it.](#)^[8] They can also export multiple calls with or without a call details file.

1. Perform a search.
2. Within the results, for those calls that you want included in the export, select the check box on the right.

The screenshot shows the AVAYA ContactStore interface. The top navigation bar includes 'AVAYA ContactStore powered by Verint Systems' and links for 'Help', 'About', 'Change Password', and 'Logout'. On the left, there is an 'Administration' section with a link to 'Administer System' and a 'Search Filters' section. The 'Search Filters' section has a 'Call Start Range' with two date-time input fields: '01/04/09 00:00:00' and '13/05/09 23:59:59'. The main area is titled 'Results' and contains a table with columns: 'Call Start', 'Len', 'Parties', 'Type', and 'Target'. There are also links for 'Select All' and 'Select None'. The table lists four call records with checkboxes in the right margin for selection.

Call Start	Len	Parties	Type	Target	
24/04/09 02:13:54	00:15	2205 (Extn2205), 2207 (Extn2207)	Outgoing	2207	<input checked="" type="checkbox"/>
24/04/09 02:14:26	00:12	3103 (Extn3103), 2205 (Extn2205)	Incoming	2205	<input checked="" type="checkbox"/>
24/04/09 02:24:27	00:09	2205 (Extn2205), 2207 (Extn2207)	Outgoing	2207	<input checked="" type="checkbox"/>
24/04/09 02:25:19	00:12	3103 (Extn3103), 2205 (Extn2205)	Incoming	2205	<input type="checkbox"/>

3. Click on the  icon.
4. Select what you want to export.

The screenshot shows a dialog box for selecting export options. It has a text input field at the top, followed by three radio buttons labeled 'Audio', 'Details', and 'Both'. Below the radio buttons is a 'Close Window' button.

- Audio
Export just an audio file for each selected call.
- Details
Export a .csv text file of call details for the selected calls.
- Both
Export both file types.

5. A menu will appear for you to browse to the folder location where you want the files exported. If you are also exporting the file details you can set the name of the .csv file at this time. Select a location and click OK.
6. The progress of the export is displayed.

The screenshot shows the same dialog box as in step 4, but with a green progress bar at the top displaying '4 / 4'. The radio buttons and 'Close Window' button are still visible.

Performance figures and data quoted in this document are typical, and must be specifically confirmed in writing by Avaya before they become applicable to any particular order or contract. The company reserves the right to make alterations or amendments to the detailed specifications at its discretion. The publication of information in this document does not imply freedom from patent or other protective rights of Avaya or others.

Intellectual property related to this product (including trademarks) and registered to Lucent Technologies have been transferred or licensed to Avaya.

All trademarks identified by the ® or ™ are registered trademarks or trademarks, respectively, of Avaya Inc. All other trademarks are the property of their respective owners.

This document contains proprietary information of Avaya and is not to be disclosed or used except in accordance with applicable agreements.

Any comments or suggestions regarding this document should be sent to "wgctechpubs@avaya.com".

© 2009 Avaya Inc. All rights reserved.

Avaya
Unit 1, Sterling Court
15 - 21 Mundells
Welwyn Garden City
Hertfordshire
AL7 1LZ
England.

Tel: +44 (0) 1707 392200
Fax: +44 (0) 1707 376933

Web: <http://www.avaya.com/ipoffice/knowledgebase>